



SRC ENERGY

**Operator:** SRC Energy  
**Well Name:** Von Trotha Bros Inc 1  
**Legal:** NENE, Section 31, Township 6N, Range 66W  
**Location:** Weld County, CO  
**API:** 05-123-05203  
**Surface:** 10.75" 40# @ 303'      **Hole Size:** 13.75"      **TOC:** Surface  
**Production:** N/A      **Hole Size:** 8.75" (305'-7676')      **TOC:** N/A  
7.875" (7676'-8900')  
**TD:** 8,900'

P&A Procedure

1. Conduct pre-job safety meeting and complete daily JSA
2. Dig out to find wellhead and check pressure
3. Cut cap off, extend surface pipe to achieve ground level
4. MIRU WO unit, ND wellhead, NU BOP, tally all pipe to be ran in well
5. Mill cement, cement btm is approximately 300' according to well history data
6. Wash run to depth that well allows
7. TOOH, remove BHA for milling
8. TIH to 6630' based off of pipe tally and pump a 400' plug (6230'-6630')
  - a. 182 sx of 15.8# class G neat 1.15 cu/ft yield cement (6230'-6630')
  - b. Wait 4 hours and tag plug
9. TIH to 4200' based off of pipe tally and pump a 200' plug (4000'-4200')
  - a. 91 sx of 15.8# class G neat 1.15 cu/ft yield cement (4000'-4200')
  - b. Wait 4 hours and tag plug
10. TIH to 600' based off of pipe tally and pump a 600' plug (0'-600')
  - a. 317 sx of 15.8# class G neat 1.15 cu/ft yield cement (0'-600')
  - b. Wait 4 hours and tag plug
11. RDMO WO unit
12. Remove extension of surface pipe. Top off if necessary.
13. Weld on cap with ID plate, inscribed with well location, and identity
14. Backfill, clean location
15. P&A complete